

Firmware aktualisieren für GIGA Vu PRO ab Version 1.0.4

Vielen Dank, dass Sie sich für ein GIGA Vu PRO entschieden haben!

Nach dem Herunterladen der Firmware xxx.zip (storage.jffs2, zImage, filesystem.cramfs usw.) aus dem Internet oder aus einer Email auf Ihren PC die Datei entpacken.

Giga Vu Pro einschalten.

USB-Kabel anschließen.

USB-Verbindung aufbauen.

Alle herunter geladenen Firmware Dateien „storage.jffs2, zImage, filesystem.cramfs usw., vom PC auf die Festplatte des GIGA Vu PRO kopieren.

Nach Beendigung des Kopiervorgangs ca. 3 Min. warten und anschließend die USB-Verbindung trennen.

Das GIGA Vu PRO ausschalten und wieder einschalten.

Nach dem Einschalten wird die neue Firmware installiert.

Bitte auf die Bildschirmanzeige achten!

So lange die Meldung „Flashing new image Please wait“ in der Anzeige steht, das GIGA Vu PRO bitte nicht ausschalten.

Zum Überprüfen wird unter Device/Gerät-> Device info/Geräteinformation –Software wird die Nummer der Firmware Version angezeigt.

JOBO Giga Vu Pro Firmware Upgrade

Thank you for your purchase of the JOBO Giga Vu Pro. The Giga Vu Pro has been designed to allow for firmware updates to enhance the performance of the unit. The instructions below will tell you how to upgrade the unit.

1. Create a folder on your computer in which to save the firmware download. Make sure the folder is easy to find.
2. Go to www.jobo.com or www.jobo-usa.com and download the latest version of firmware. Download the firmware into your newly created folder. The download will be a ZIP file and will need to be extracted before installing the data onto the Giga Vu Pro.
3. Extract the file following your extraction software instructions. We recommend saving the extracted files in the same folder you created to store the download. This makes it easy to find the extracted files.
4. The extracted files will be in a folder bearing the same name as the ZIP file you downloaded from the internet. Open this folder. There should be several files in it. If there are not, delete both the ZIP folder and the unzipped folder, and redo the downloading process. Sometimes data can be lost or corrupted during transfer and this will prevent a proper update.
5. Before connecting the Giga Vu Pro to the computer, power it up and check the current version of firmware on the unit.
6. Connect AC power to the Giga Vu Pro and then connect the USB connection. Warning! Do not try this procedure on battery power! Damage to the Giga Vu Pro that is not covered under warranty will occur! Use the upper USB connection on the Giga Vu Pro and be sure to connect the USB cable directly into the computer. Do not go through a hub.
7. Engage the USB connection on the Giga Vu Pro and wait for the icon to appear in MY COMPUTER (Windows) or on the DESKTOP (MAC).
8. Open the folder containing the extracted firmware files. SELECT ALL files and drag and drop them onto the GIGA Vu Pro icon. It is important that you drag the individual files onto the Giga Vu Pro. Dragging the folder icon will not work.
9. Once the upgrade is complete SAFELY REMOVE (Windows) or EJECT the Giga Vu Pro from the computer.
10. Power down the Giga Vu Pro.
11. Power the Giga Vu Pro back up. You should get the FLASHING NEW IMAGE PLEASE WAIT message. The Giga Vu Pro is now upgrading the firmware. Please wait. Do not disturb the unit during the upgrade. It may take 10 minutes or longer to complete the upgrade. Warning! Power loss, static shock or physical damage during the upgrade will seriously damage the Giga Vu Pro! This damage is not covered under warranty.
12. Check the Giga Vu Pro firmware on the unit, it should be upgraded. If not, try the upgrade again. Sometimes bad data can cause a firmware failure. If the problem persists, contact JOBO for assistance.